



Marketing Name **QCast Mirror HDMI Wireless Dongle**

Unique selling point

- * HIGH SPEED TRANSMISSION QUALITY: 2.4/5G Dual Band WiFi, up to 4K@30p video quality
- * FAST SETUP TO DISPLAY: screen mirroring with no software required
- * OTA UPDATE & EFFORTLESS MAINTENANCE: Over-the-Air (OTA) update capability with the latest firmware
- * SUPPORT OS SYSTEM: iOS 12+ and Mac OS 10.12+ as well as Android 9+ and Windows 7+ and Chrome OS

Model Name	QP30
Dimensions(W x H x D)	97.2 x 12 x 32 mm
Input Terminals	USB-C (only for power supply and system recovery by SW tool)
Output Terminals	HDMI 1.4b
Weight	32g approx.
Wireless Standard	IEEE 802.11a/b/g/n/ac
Security	WPA/WPA2
LED	Blue LED indication for Power
Output Resolution	1280x720@60hz 1280x720@50hz 1920x1080@60Hz 1920x1080@50Hz 4096x2160@30hz 3840x2160@30hz
Frequency Band	2.4G/5G*
Color	White
CPU	AM8270
DRAM	DDR3 512MB
NAND	256MB
Power	DC 5V/1.5A, through USB-C port
Video support	Max. 4K@30p video decode
Package	QCast Mirror Dongle x 1 USB-C cable x 1 HDMI extend cable x 1 Quick start guide x 1

System Requirement

PC	
<u>Windows OS</u>	Windows 7 and later with Miracast support *Mirror Screen support depends on Wi-Fi module and graphics chipset.
<u>Mac OS</u>	Mac OS X 10.12 and above with Mirror Screen support *Recommended Models: Mac Book series and iMac series after E/2015
<u>Chrome OS</u>	for cast mirror support
Tablet/SmartPhone	
<u>iOS</u>	iOS12 and later with Mirror Screen support
<u>Android</u>	Android 9 above with Mirror Screen support

Features

Mirror Screen	Screen mirroring from mobile devices with Mirror Screen supported OS
Advanced Settings	Language: sets the language for Advanced Settings page Password: changes the Wi-Fi password for the projector 2.4G/5G: selects 2.4G or 5G Wi-Fi (only available on Web Setting) Resolution: sets the output resolution. Upgrade: updates to the latest firmware Reset to default: returns all settings to the factory preset values. Restart System: reboot QCast Mirror Dongle

- * 5G Wifi only support Band I (5.150-5.250GHz)
- * Transmission quality depends on the Wi-Fi environment and the Mirror function compatibility of mobile devices from different brands. In order to guarantee the best transmission quality, please see compatible mobile device list on official website.
- * Please make sure your device is upgraded to proper version OS and with mirror function support as well.
- * For further information, please visit: // www.benq.com/

Operating Instruction

How to Setup

- Plug USB-C cable into QCast Mirror
- Plug HDMI as signal output to Projector
- Plug USB type A (5V/1.5A) with Projector for Power supply
- Select HDMI Source on Projector, then Standby page will be shown

How to Connect

- Windows: Click Mirror Screen function embedded in your mobile device to start projection
- Android/iOS/Mac OS: Pair QCast Mirror and your device via SSID/password in advanced, then click Mirror Screen function embedded in your mobile device to start projection.

How to enter Advanced Settings

- Pair QCast Mirror and your device via SSID/password, and open web browser in your device to link to <http://192.168.168.1>, then start settings.
- Please restart QCast Mirror Dongle after settings are changed.

Product Photo

